### **Technical data sheet**

### 0° socket, protective contact, single

**Item number: 6120010** 



Power socket, single 0°, with increased touch protection with screwless terminals, 2-pin, 16 A, 250 V~, with connection terminals to IEC 60884-1.

For installation in Rapid 45 trunking, device installation trunking, service poles, underfloor systems and desk boxes.







Polycarbonate

М	_	_	4.				4-
IVI	ы	S	Tf	31	. (	112	па

Item number	6120010
Description 1	Socket 0°, single
Description 2	protective contact
Manufacturer	OBO
Dimension	250V, 10/16A
Colour	Pure orange; RAL 2004
Material	Polycarbonate
Smallest sales unit	1
Unit of quantity	Piece
Weight	4.2 kg
Weight unit	kg/100 pc.
CO Footprint (GWP) Cradle-to- Gate	0,1974 kg COe / 1 Piece


# **Technical data sheet**

### 0° socket, protective contact, single


**Item number: 6120010** 



#### Dimensions



Width	45 mm
Height	45 mm



#### Technical data

Cover	Central plate
Closable	no
Connection type	Screwless terminal
Number of units	1
Number of modules (for modular construction)	0
Number of switchable sockets	0
Number of poles	2
Printed label/coding	Without printing
Version for	single 0°
Surface version	Matt
Version for	SCHUKO
Ejection mechanism	no
Fastening type	Lock
Labelling panel	no
Operating temperature, max.	40 °C
Operating temperature, min.	-5 °C
increased touch protection	yes
Error current protection	no
For more difficult conditions (according to VDE)	no
Power reserve	no
Halogen-free	yes
Insulated installation	no
Hinged cover	no
Coding	no
Warning light	no
With on/off switch	no
With fine-wire fuse	no

# **Technical data sheet**

# 0° socket, protective contact, single

Item number: 6120010



Technical data		
	With functional lighting	no
	With orientation lighting	no
	Mounting type	Device installation duct
	Nominal voltage	250 V
	Nominal current	16 A
	Protection rating	Other
	Special power supply	Without special power supply
	Socket version	Protective contact
	Socket angle	0°
	Depth	42 mm
	Transparent	no
	Rotated central insert	no
	Approvals	VDE
	Surge protection	no